

**NEW!**

**HARRIS**

# Pro3000 Tone & Probe Kit

**THE professional tool you need for tracing and toning wire or cable**

Harris' Pro3000 Tone and Probe Kit is THE professional kit you need for tracing and toning wire or cable. Use it on de-energized AC wire, telephone/twisted pair wire, all voice and data category rated cable, all coax cable, speaker wire, security wire, virtually any cable or wire! All in a durable nylon pouch with three pockets and extra large belt clip.

## PRO3000 Probe

Ergonomic, sleek design is easy to handle and use. Large speaker on the probe makes the tone easier to hear through walls, enclosures, wood or plaster. A recessed on/off button helps prevent it accidentally being turned on in pouch. Accommodates a headset (sold separately) for use in noisy environments.

### Top Features:

- Loud large speaker amplifies tone through walls, enclosure, wood or plaster
- Easy-to-use adjustable volume control dial
- "Quick-twist" tip for easy replacement
- FREE Spare Tip inside

## PRO3000 Tone Generator

Easy to operate with a single button and patented SmartTone™ Technology built inside! By touching the wires together and momentarily shorting a cable pair, the SmartTone tone generator will change the sound of the tone if you are clipped on to the correct pair. This allows you to verify and positively identify that you have located the correct wire pair. SmartTone provides 5 distinct tones to insure that there is no doubt that you are using the correct wires.

### Top Features:

- SmartTone technology
- Send tone signal up to 10 miles on most cables
- Line cord features Angled Bed-of-Nails clips and ruggedized RJ-11 plug for direct access to phone and data jacks without adapters
- External switch lets you select solid or alternating tone options, indicated with solid or flashing LEDs
- Continuity testing
- Line polarity confirmation





### Ordering Information

Part Number	Description
26000-900	Pro3000 Tone & Probe Kit

### Pro3000 TONER Specifications

#### USER INTERFACE:

Slide switch selects Continuity or Tone Mode  
 Push button Switch selects SOLID, ALT or OFF  
 Tone Mode LED  
 Continuity/Polarity LED

#### FREQUENCY:

SOLID: 1000 Hz nominal  
 ALT: 1000/1500 Hz nominal  
 Over Voltage Protection: 60 Vdc in Toner/Polarity Mode  
 Output Power in Tone Mode: 8 dbm into 600 ohms

**Output Voltage Level in Continuity Mode:** 8 Vdc with fresh battery

**Battery:** 9V Alkaline

**Temperature:** Operating: -20C to 60C, Storage: -40C to 70C

**Case Dimensions:** 2.7in. x 2.4in. x 1.4in. (6.9cm x 6.1cm x 3.6cm)

### Pro3000 PROBE Specifications

#### USER INTERFACE:

ON/OFF Pushbutton  
 Volume Dial  
 Replaceable Tip  
 3.5 mm Earphone Jack

**Battery:** 9V Alkaline

**Temperature:** Operating: -20C to 60C, Storage: -40C to 70C

**Case Dimensions:** 9.8in. x 1.6in. x 1.3in. (24.9cm x 4.1cm x 3.3cm)

Product design and specifications subject to change without notice. All trademarks belong to their respective companies.



Fluke Networks | 809 Calle Plano | Camarillo, CA 93012-8519 USA  
[www.harristools.flukenetworks.com](http://www.harristools.flukenetworks.com) 1-800-437-2266 or 1-805-987-9511